


Small-Signal Schottky Barrier Diode



Features

- High reliability
- Fast Switching
- Low Forward Voltage Schottky Rectifier

Mechanical Data

- **Package:** SOD323
- **Terminals:** Tin plated leads, solderable per J-STD-002 and JESD22-B102
- **Polarity:** Cathode line denotes the cathode end
- **Marking:** L9

■ Maximum Ratings ($T_a=25^\circ\text{C}$ Unless otherwise specified)





PARAMETER	SYMBOL	UNIT	Conditions	VALUE
Repetitive peak reverse voltage	V_{RRM}	V		30
Peak forward surge current	I_{FSM}	A	$t_p < 1s$	0.6
Average forward current	I_{FAV}	mA		200
Power dissipation	P_{tot}	mW		200
Maximum junction temperature	T_j	$^\circ\text{C}$		-55 to +125
Storage temperature range	T_{stg}	$^\circ\text{C}$		-55 to +150

■ Electrical Characteristics ($T_a=25^\circ\text{C}$ Unless otherwise specified)

PARAMETER	SYMBOL	UNIT	Conditions	VALUE
Maximum Forward voltage	V_F	V	$I_F=0.1\text{mA}$	0.24
			$I_F=1\text{mA}$	0.32
			$I_F=10\text{mA}$	0.40
			$I_F=30\text{mA}$	0.50
			$I_F=100\text{mA}$	1.00
Maximum Reverse current	I_R	μA	$V_R=25\text{V}$	2
Minimum Breakdown voltage	$V_{(BR)}$	V	$I_R=10\mu\text{A}$	30
Maximum Diode capacitance	C_D	pF	$V_R=1\text{V}, f=1\text{MHz}$	10
Maximum Reverse recovery time	t_{rr}	ns	$I_F=I_R=10\text{mA}, I_{RR}=1\text{mA}, R_L=100\Omega$	5



■ Characteristics (Typical)






BAT54WS

Ordering Information (Example)


PREFERRED P/N	PACKING CODE	UNIT WEIGHT(g)	MINIMUM PACKAGE(pcs)	INNER BOX QUANTITY(pcs)	OUTER CARTON QUANTITY(pcs)	DELIVERY MODE
BAT54WS	F2	Approximate 0.0033	3000	30000	120000	7" reel

Outline Dimensions



Symbol	Min. (mm)	Max. (mm)
A		1.000
A1	0.000	0.100
A2	0.800	0.900
b	0.250	0.400
c	0.080	0.150
D	1.200	1.400
E	1.600	1.800
E1	2.500	2.700
L	0.475REF	
L1	0.250	0.400
θ	0°	8°

Soldering Footprint





BAT54WS

Disclaimer

The information presented in this document is for reference only. Yangzhou Yangjie Electronic Technology Co., Ltd. reserves the right to make changes without notice for the specification of the products displayed herein to improve reliability, function or design or otherwise.

The product listed herein is designed to be used with ordinary electronic equipment or devices, and not designed to be used with equipment or devices which require high level of reliability and the malfunction of which would directly endanger human life (such as medical instruments, transportation equipment, aerospace machinery, nuclear-reactor controllers, fuel controllers and other safety devices), Yangjie or anyone on its behalf, assumes no responsibility or liability for any damages resulting from such improper use of sale.

This publication supersedes & replaces all information previously supplied. For additional information, please visit our website [http:// www.21yangjie.com](http://www.21yangjie.com) , or consult your nearest Yangjie's sales office for further assistance.