


# BAV19W THRU BAV21W

## Small-Signal Switching Diodes



### Features

- $V_R$  100V/150V/200V
- $I_{FAV}$  200mA

### Typical Applications

- Extreme fast switches

### Mechanical Data

- **Package:** SOD123
- **Terminals:** Tin plated leads, solderable per J -STD-002 and JESD22-B102
- **Polarity:** Cathode line denotes the cathode end

	Marking
BAV19W	A8
BAV20W	T2
BAV21W	T3

### ■ Maximum Ratings ( $T_a=25^\circ\text{C}$ Unless otherwise specified)

PARAMETER	SYMBOL	UNIT	Conditions	VALUE
Repetitive peak reverse voltage	$V_{RRM}$	V		BAV19W 120
				BAV20W 200
				BAV21W 250
Average forward current	$I_{FAV}$	mA		200
Power dissipation	$P_{tot}$	mW		400
Maximum junction temperature	$T_j$	$^\circ\text{C}$		-65 to +150
Storage temperature range	$T_{stg}$	$^\circ\text{C}$		-65 to +150

### ■ Electrical Characteristics ( $T_a=25^\circ\text{C}$ Unless otherwise specified)

PARAMETER	SYMBOL	UNIT	Conditions	VALUE
Maximum Forward voltage	$V_F$	V	$I_F=100\text{mA}$	1.0
			$I_F=200\text{mA}$	1.25
Maximum Reverse current	$I_R$	nA	BAV19W $V_R=100\text{V}$	100
			BAV20W $V_R=150\text{V}$	
			BAV21W $V_R=200\text{V}$	
Minimum Breakdown voltage	$V_{(BR)}$	V	BAV19W $I_R=10\mu\text{A}$	100
			BAV20W $I_R=10\mu\text{A}$	150
			BAV21W $I_R=10\mu\text{A}$	200
Maximum Diode capacitance	$C_D$	pF	$V_R=0\text{V}, f=1\text{MHz}$	5
Maximum Reverse recovery time	$t_{rr}$	ns	$I_F=I_R=30\text{mA}, R_L=100\Omega, I_{RR}=3\text{mA}$	50



# BAV19W THRU BAV21W

## Ordering Information (Example)

PREFERRED P/N	PACKING CODE	UNIT WEIGHT(g)	MINIMUM PACKAGE(pcs)	INNER BOX QUANTITY(pcs)	OUTER CARTON QUANTITY(pcs)	DELIVERY MODE
BAV19W Thru BAV21W	F2	Approximate 0.011	3000	30000	120000	7" reel

## Characteristics(Typical)

Fig.1 Total Capacitance




Fig.2 Forward Voltage vs Ambient Temperature






Fig.3 Reverse Current vs Reverse Voltage






## BAV19W THRU BAV21W

### ■ Outline Dimensions



### ■ Soldering Footprint





## BAV19W THRU BAV21W

---

### Disclaimer

The information presented in this document is for reference only. Yangzhou Yangjie Electronic Technology Co., Ltd. reserves the right to make changes without notice for the specification of the products displayed herein to improve reliability, function or design or otherwise.

The product listed herein is designed to be used with ordinary electronic equipment or devices, and not designed to be used with equipment or devices which require high level of reliability and the malfunction of which would directly endanger human life (such as medical instruments, transportation equipment, aerospace machinery, nuclear-reactor controllers, fuel controllers and other safety devices), Yangjie or anyone on its behalf, assumes no responsibility or liability for any damages resulting from such improper use of sale.

This publication supersedes & replaces all information previously supplied. For additional information, please visit our website [http:// www.21yangjie.com](http://www.21yangjie.com) , or consult your nearest Yangjie's sales office for further assistance.