

PRODUCT SPECIFICATION



Part No. : JH-5630W12JC2240-T16A High Power LED

Catalog


1.Product Features	P2
2.Dimensions	P2
3.Absolute Maximum Rating	P3
4.Optical Character	P3
5.Optical Character Curves	P4
6.Spectrum Curves	P5
7.Viewing Angle Curves	P5
8.Cautions	P6



1.Product Features

- High Brightness White LED
 Plane Package
- Viewing Angle 120 Degree
- Chip Material: AlGaInP
- RoHS Compliant

2.Dimensions



Notes:

- 1. All dimensions are in millimeters.
- 2. Tolerance is ±0.1mm unless otherwise noted.



3.Absolute Maximum Rating @ Ta=25° C

Parameter	Symbol	Maximum Rating	Unit	
Continuous Forward Current	IF	150	mA	
Peak Forward Current (1/10 Duty Cycle, 0.1ms Pulse Width)	IFp	300	mA	
Reverse Voltage	VR	5	V	
Power Dissipation	PD	0.5	W	
Electrostatic Discharge	ESD	1000	V	
Operating Temperature Range	TOPR	-25°C to +60°C		
Storage Temperature Range	TSTG	-35°C to +80°C		
Lead Soldering Temperature	TSOL	260°C		

4.Optical Character @ Ta=25° C

Parameter	Symbol	Color	Min.	Тур.	Max.	Unit	Test Condition
Forward Voltage	VF	W	3.0	3.2	3.4	V	I _F =150mA
Luminous Flux	Ф	W	60	70	80	Lm	I _F =150mA
Color Temperature	Tc	W	4000	4500	5000	K	I _F =150mA
Reverse Current	IR		0		10	μΑ	V _R =5V
Viewing Angle	201/2				120	deg	I _F =150mA
Recommend Forward Current	IF(rec)	W			150	mA	


Notes:


Measurement tolerance of forward voltage±0.1V





5. Optical Character Curves

(25 ° Ambient Temperature Unless Otherwise Noted)













6. Spectrum Curves



7. Viewing Angle Curves

Radiation Characteristic

IF=150mA





8. Cautions


1. Electrostatic Treatment

Do a full range of anti-static measures (such as: anti-static ring, anti-static clothes, machine, equipment grounding wire, etc.)



2. Heat Dissipation

- A. It is recommend to configure reasonable heat dissipation device for the product.
- The best working temperature range of the product is 40-60°. It is recommended to control the working temperature of the product within a reasonable range.



3. Installation Conditions

reference

A. Do not exert any pressure on the LED area during the use of the led beads, such as below:



