

RC832HD RC-HD FPV 5.8G 48CH HDMI

Description:

Sensitivity: $\leq -93\text{dBm}$

Working Frequency: ISM 5.8GHz

Available Channel: 48CH

Power supply: DC 6-24V

Consumption Current: 200mA, Max

Antenna input Impedance: 50ohm Typ.

Antenna Connector: RP-SMA

Antenna Gain: 2dBi

Video Output Level: 1.0Vp-p Typ, 75K Ω

Audio Output Level: $\geq 1.0\text{Vp-p}$ Typ 10K Ω

Audio Carrier: 6.5MHz

Type Standard: NTSC/PAL

Dimension (L x W x H): 80x65x15 mm

Weight: 120g

Features:

48 channels: Cover A, B, E, F, R bands and L band (Airwave band), 6 bands and all frequencies compactable;

Two switching buttons: CH button for frequency channels switching, FR button for frequency bands switching;

Two digits display: one for CH and the other for FR, real-time positioning which frequency band and which channel received;

Power off memory: Replay the very last frequency band and channel

Independent video and audio signal outputs





